

Our Case No. 9281/3751
Client Reference No. FC US99053

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE
APPLICATION FOR UNITED STATES LETTERS PATENT

INVENTOR: SHIGENORI YAMASAKI
KOICHI ABE

TITLE: COMMUNICATION APPARATUS
CAPABLE OF REGISTERING ID
CODES APPROPRIATED TO
PORTABLE TRANSMITTERS BY
OPERATING THE TRANSMITTERS

ATTORNEY: Gustavo Siller, Jr.
BRINKS HOFER GILSON & LIONE
P.O. BOX 10395
CHICAGO, ILLINOIS 60610
(312) 321-4200

EXPRESS MAIL NO. EL 513 141 093 US

DATE OF MAILING 9/11/60

09654459-090100

COMMUNICATION APPARATUS CAPABLE OF REGISTERING ID CODES
APPROPRIATED TO PORTABLE TRANSMITTERS BY OPERATING THE
TRANSMITTERS

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to a communication apparatus, and particularly relates to a communication apparatus wherein information signals containing ID (Identification) code are transmitted from a portable transmitter, and a controlled device is controlled in the event that the ID code within the information signals received with a receiver match a registered reference code, wherein the ID code of the portable transmitter is registered by the user.

2. Description of the Related Art

Keyless entry devices for automobiles are known as an example of communication apparatuses comprising a portable transmitter and a receiver, wherein upon transmitting of information signals containing ID code by operating the operating unit of the portable transmitter, the ID code is extracted from the information signals received at the receiver side, and wherein the controlled device can be controlled in the event that that ID code matches the reference code already registered thereto.

0054469 090100

[illegible][illegible][illegible][illegible]

The portable transmitter 70 and the receiver 80 with the above configurations each operate as described next.

On the other hand, with regard to the receiver 80, the receiving unit 81 receives the transmitting signals through the receiving antenna 87, and restores the transmitting code.

On the other hand, with regard to the receiver 80, the receiving unit 81 receives the transmitting signals through the receiving antenna 87, and restores the transmitting code.

In this case, the ID code appropriated to each portable transmitter 70 in the known keyless entry device is stored in the ID code storing unit 74 of the portable transmitter 70 at the time of manufacturing and is unique to the portable transmitter 70, and the reference code stored in the reference code storing unit 83 of the receiver 80 is stored as the reference code by extracting the ID code transmitted from the portable transmitter 70 and writing the extracted ID code to the reference code storing unit 83.

Generally, users using a keyless entry device prefer that there is no compatibility between the portable transmitter 70 of the user and the portable transmitter 70 of others, so the ID code of the portable transmitter 70 of

the user must differ from the ID code of the portable transmitter 70 of others.

One problem is that the portable transmitter 70 of the known keyless entry device requires an ID code writing device, since ID codes which differ for each vehicle are written to the ID code storing units 74 by the manufacturer at the time of manufacturing. An additional problem is that ID code management becomes complicated.

SUMMARY OF THE INVENTION

The present invention has been made in view of the known portable transmitter and receiver combination, and it is an object thereof to provide a communication apparatus enabling ID codes appropriated to portable transmitters to be registered by operating the portable transmitter.

In order to achieve the above objects, a first aspect of the present invention is a communication apparatus including: a portable transmitter, having at least one operating switch, a first storing unit wherein an ID code is registered, a first control unit, and a transmitting unit. The ID code is made up of a plurality of ID code sections, each ID code section corresponding to an operation of the operating switch. The portable transmitter also comprises an ID registration mode setting mechanism. When the first control unit is set to the ID registration mode by the ID

0954459-090100

In other embodiments, the operating switch may be operated multiple times and/or the ID code sections may be supplied sequentially to the first storing unit.

Further, in order to achieve the above objects, a third aspect of the present invention is a communication apparatus

11

✓

Also, according to the second aspect, the formed ID code sections are sequentially stored in a second storing

unit formed of RAM, and at the point that all ID code sections are stored in the second storing unit, all ID code sections are joined and read out from the second storing unit, and transferred and registered as ID code to the first storing unit, so in the event that ID code registration has been aborted, all that is necessary is to erase the ID code sections stored in the RAM, so there is no effect on the first storing unit.

Also, according to the third aspect, the formed ID code sections are sequentially stored in a second storing unit formed of RAM, and at the point that the last ID code section is formed, the ID code sections stored in the second storing unit are read out from the second storing unit and joined with the last ID code section, and transferred and registered as ID code to the first storing unit, so the process of storing and reading the last ID code section to and from the second storing unit can be omitted, which is efficient.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a block configuration diagram illustrating a first embodiment of the communication apparatus according to the present invention, and illustrates the configuration of the portable transmitter;

Fig. 2 is a block configuration diagram illustrating an

0054459-090100

example of the operating procedures for writing a reference code to the reference code storing unit of the receiver, using the portable transmitter:

Fig. 9 is a block diagram illustrating an example of the configuration of a portable transmitter used with a known keyless entry apparatus; and

Fig. 10 is a block diagram illustrating an example of the configuration of a receiver used with a known keyless entry apparatus.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Sub 1
The following is a description of the embodiments of the present invention, with reference to the drawings. First Embodiment

Figs. 1 and 2 are block diagrams illustrating a first embodiment of the communication apparatus according to the present invention, wherein Fig. 1 is a block diagram illustrating the configuration of the portable transmitter 10, and Fig. 2 is a block diagram illustrating the configuration of the receiver 20, illustrating an example of a keyless entry device wherein the communication apparatus is made up of a portable transmitter 10 and a receiver 20.

As shown in Fig. 1, the portable transmitter 10 is provided with an operating switch unit (operating SW) 1 having one or more operating switches, a control unit (first

The operating switch unit 1, control unit 2, transmitting unit 3, EEPROM 4, ID code storing unit 4₁, display unit 5, and transmitting antenna 6, are connected as shown in Fig. 1. Also, the door lock switch 1₁, door unlock switch 1₂, trunk open switch 1₃, and panic switch 1₄ of the operating switch unit 1 are connected as shown in Fig. 1, and the function code converting unit 2₁, transmitting code forming unit 2₂, mode control unit 2₃, ID code generating unit 2₄, clock signal generating unit 2₅, and counter 2₆ of the control unit 2 are also connected as shown in Fig. 1.

On the other hand, as shown in Fig. 2, the receiver 20 comprises a receiver 11, control unit (second control unit) (CPU) 12, EEPROM (second storing unit) 13, and receiving antenna 14. In this case, the control unit 12 has a built-

Then, the receiving unit 11, control unit 12, EEPROM 13, receiving antenna 14, and ignition key 15, are connected as shown in Fig. 2. Also, the signal processing unit 12₁ and control signal generating unit 12₂ of the control unit 12 are connected as shown in Fig. 2, and the reference code storing unit 13₁ and function code storing unit 13₂ of the EEPROM 13 are also connected as shown in Fig. 2.

Now, at the point that the user has obtained the portable transmitter 10 and receiver 20 of the above configuration (point of product purchase), no ID code has yet been registered to the ID code storing unit 4₁ of the portable transmitter 10, nor has a reference code been registered to the reference code storing unit 13₁ of the receiver 20. Accordingly, there is the need for the user to register an ID code to the ID code storing unit 4₁ of the portable transmitter 10, and use the portable transmitter 10 to which the ID code has been registered to store the reference code in the reference code storing unit 13₁ of the receiver 20, before using the portable transmitter 10 and receiver 20.

Sub-
C2

The user performs a predetermined operation using one or more operating switches of the operating switch unit 1 of the portable transmitter 10, e.g., first operating the trunk opening switch 1₃, and within 100 milliseconds of this operation presses both the trunk opening switch 1₃ and the door lock switch 1₁ for 1 second or more, whereby the mode control unit 2₃ detects that this predetermined operation has been made, and sets the control unit 2 in the ID registration mode. Once the control unit 2 is set in the ID registration mode, the counter 2₆ is reset, the first count of clock signals supplied from the clock signal generating unit 2₅ is started at the counter 2₆, and a first pulse signal is supplied to one LED of the display unit 5 from the mode control unit 2₃, e.g., the red LED. The red LED is lit multiple times for 200 milliseconds at 500 millisecond intervals due to the first pulse signals being supplied, thereby notifying the user that the portable transmitter 10

Sub A3

Next, the user operates the latter-operated switch of the operating switch unit 1 of the portable transmitter 10, the door lock switch 1₁ for example, for 100 milliseconds or longer, following which the operation is stopped, which causes a second pulse signal to be supplied to another LED of the display unit 5 from the ID code generating unit 2₄, e.g., the green LED; and the green LED is lit for 500 milliseconds only one time. Then, at the point that the lighting of the green LED is finished, the first count value of the clock signal is determined at the counter 2₆, the determined count value is supplied to the ID code storing unit 4₁ of the EEPROM 4 through the ID code generating unit 2₄, and is stored as the first ID code section. At this time, the counter 2₆ is reset, subsequently starts the second count of clock signals being supplied, and the first pulse signals are supplied multiple times from the ID code generating unit 2₄ to the red LED as in the case above, so that the red LED is lit intermittently.

~~Next, the user operates the door lock switch 1₁ again for 100 milliseconds or more, and then stops the operation, which causes the second pulse signal to be supplied from the~~

See b7
D

Sub 1

The first through third ID code sections stored in the ID code storing unit 41 form one ID code as a whole.

In this case, the first through third ID code sections

sequentially stored in the ID code storing unit 4_1 (three count values) are each made up of 8 bits, and one of the 256 combinations for data values from 00000000 through 11111111 is stored in the ID code storing unit 4_1 for each ID code section.

Following resetting of the counter 2_6 , the first count of the clock signal performed by the counter 2_6 sequentially changes from 00000000 to 11111111 each time a clock signal is applied, returns to 00000000 when 11111111 is reached, and then changes again toward 11111111. Then, when the first lighting of the green LED ends, the count value of the counter 2_6 is stored in the ID code storing unit 4_1 as the first code section.

Subsequently, the counter 2_6 is reset, and the second and third counts of the clock signal performed by the counter 2_6 act in the same manner as with the previous case, and when the second lighting of the green LED ends, the count value of the counter 2_6 is stored in the ID code storing unit 4_1 as the second code section, and when the third lighting of the green LED ends, the count value of the counter 2_6 is stored in the ID code storing unit 4_1 as the third code section.

In this way, the first through third code sections (count values) stored in the ID code storing unit 4_1 of the portable transmitter 10 according to the first present

00000000 00000000 00000000 00000000

embodiment are set randomly by switch operation timing by the user. Accordingly, with regard to the ID code formed by the entirety of the first through third code sections, the probability that the ID code registered to one portable transmitter 10 and the ID code registered to another portable transmitter 10 using the same registering means match is extremely small, and thus a portable transmitter 10 with no compatibility can be obtained.

In this case, with the portable transmitter 10, in the event that the control unit 2 enters the ID registration mode and 10 seconds elapse, the control unit 2 automatically reverts from the ID registration mode to the normal mode, and the blinking of the red LED on the display unit 5 ends.

*Sub
all*

~~Then, as shown in Fig. 3, at the point that the third count value is determined and the third lighting of the green LED ends, and registration of the ID code is performed to the ID code storing unit 4₁, the control unit 2 reverts from the ID registration mode to the normal mode even in the event that 10 seconds have not elapsed since being set to the ID registration mode.~~

Next, Fig. 4 is an action describing diagram illustrating an example of a case wherein the ID code cannot be registered at the time of registering the ID code to the ID code storing unit 4₁ of the portable transmitter 10.

The action in the event that the ID code cannot be

Sub
A.4

As shown in Fig. 4, the operating procedures up to the control unit 2 of the portable transmitter 10 being set to the ID registration mode by execution of predetermined operations of the operating switch unit 1 by the user, are the same as the operating procedures already described with reference to Fig. 3.

Next, the user operates the latter-operated switch of the operating switch unit 1 of the portable transmitter 10, the door lock switch 1₁ for example, for 100 milliseconds or longer, following which the operation of the door lock switch 1₁ is stopped, which causes a second pulse signal to be supplied to the green LED of the display unit 5 from the ID code generating unit 2₄, and the green LED is lit for 500 milliseconds. Then, at the point that the lighting of the green LED is finished, the first count value of the clock signal is determined at the counter 2₆, the determined count value is supplied to the ID code storing unit 4₁ through the ID code generating unit 2₄, and is stored as the first ID code section in the ID code storing unit 4₁. At this time, the counter 2₆ is reset, subsequently starts the second count of clock signals being supplied, and the first pulse signals are supplied multiple times from the ID code generating unit 2₄ to the red LED as in the case above, so that the red LED is lit intermittently.

09-6489-090103

Another state wherein the ID code is not registered to the ID code storing unit 4₁ is a case wherein the first and second count values are each determined, following which the control unit 2 automatically reverts from the ID registration mode to the normal mode.

Sub 1
Pa S
t

Next, Fig. 5 is a block diagram illustrating a second embodiment of the communication apparatus according to the present invention, and is a block diagram illustrating the configuration of a portable transmitter 10'.

As shown in Fig. 5; the only difference between the configuration of the portable transmitter 10' according to

the second embodiment (hereafter referred to as "portable transmitter 10'") and the configuration of the portable transmitter 10 according to the first embodiment (hereafter referred to as "portable transmitter 10") is that the portable transmitter 10' is provided with RAM (temporary storing unit, i.e., second storing unit) 7, and the RAM 7 is joined with the ID code generating unit 2₄, whereas the portable transmitter 10 does not have such a RAM 7, and other wise there is no configuration difference between the portable transmitter 10' and the portable transmitter 10. Accordingly, further description of the configuration of the portable transmitter 10' will be omitted.

Also, the configuration of the receiver 20 in the second embodiment is the same as the configuration of the receiver 20 according to the first embodiment shown in Fig. 2, so the receiver 20 according to the second embodiment is omitted from the drawings.

With the portable transmitter 10' having the above configuration, description of the operating procedures for registering the ID code to the ID code storing unit 4₁ (first storing unit) with reference to Fig. 3 is as follows.

The series of actions up to the control unit 2 of the portable transmitter 10 being set to the ID registration mode by the user executing predetermined operations of the operating switch unit 1 is the same as the series of actions

09654459 090100

already described with reference to Fig. 3.

Sub A10
Next, the series of actions of the user operating the latter-operated switch of the operating switch unit 1 of the portable transmitter 10 and the subsequent ending of operation of the switch leading up to the determining of the first count value of the clock signal at the counter 26, is also the same as the series of actions already described with reference to Fig. 3.

Sub A11
Then, at the point that the first count value is determined, the determined count value is supplied to the RAM 7 through the ID code generating unit 24, and is stored in the first storing area of the RAM 7 as the first ID code section. Subsequently, the counter 26 is reset, then starts the second count of clock signals being supplied, and the first pulse signals are supplied multiple times from the ID code generating unit 24 to the red LED as in the case above, so that the red LED is lit intermittently.

Sub A12
Next, the series of actions of the user operating the latter-operated switch of the operating switch unit 1 of the portable transmitter 10 the second time, and the subsequent ending of operation of the switch leading up to the determining of the second count value of the clock signal at the counter 26, is also the same as the series of actions already described with reference to Fig. 3.

Sub A13
~~Then, at the point that the second count value is~~

Sub 1
214

Then, at the point that the third count value of the clock signal is determined, the count value is supplied to the RAM 7 through the ID code generating unit 24, and is stored in the third storing area of the RAM 7 as the third ID code section.

Subs.

and supplied to the ID code storing unit 4₁ of the EEPROM 4 as an ID code, and thus registered.

In this case, the first through third ID code sections sequentially stored in the first through third storing areas of the RAM 7 (three count values) are each made up of 8 bits as with the above first embodiment, and one of the 256 combinations for data values from 00000000 through 11111111 is stored in the first through third storing areas.

Incidentally, with the above embodiment, first through third storing areas are provided in the RAM 7 of the portable transmitter 10', and the first through third ID code sections are respectively stored in the first through third storing areas in sequence, following which the first through third ID code sections are read out and joined, and registered to the ID code storing unit 4₁ as an ID code.

Third Embodiment

Sub
Alt 1
Conversely, a third embodiment which has the same configuration as that of the second embodiment shown in Fig. 5 registers ID codes by the operation shown in Fig. 7. That is to say, only first and second storing areas are provided in the RAM 7, and the first and second ID code sections are respectively stored in the first and second storing areas in sequence, following which, at the point that the third count value is determined by the ID code generating unit 2₄, and the third ID code section is thus obtained, this third ID

00000000 11111111

In this case, in the event that the number of ID code sections making up the ID code is 4 or more, the ID code sections excluding the last ID code section are sequentially stored in the RAM 7, and at the point that the last ID code is obtained, this last ID code is not stored in the RAM 7 but rather held in the ID code generating unit 24, and at the point that the ID code sections excluding the last ID code section are read out from the RAM 7 ^{and} the last ID code section is joined to the read ID code sections so as to form an ID code, and this ID code is stored and registered to the ID code storing unit 41.

Also, with this portable transmitter 10' as well, in the event that 10 seconds elapse since the control unit 2 has been set to the ID registration mode, or in the event that registering of the ID code to the ID code storing unit 4₁ is completed, the control unit 2 automatically reverts from the ID registration mode to the normal mode.

In this way, in the second and third embodiments as

On the other hand, an example of the action in the event that the ID code cannot be registered to the ID code storing unit 41 with the portable transmitter 10' will now be described.

~~Now, though the arrangement of the operating procedures for setting the first control unit 2 of the portable transmitter 10 and 10' to the ID registration mode according to the first through third embodiments involve a switch of the operating switch unit 1 being operated while another~~

Sub
A 18

Also, according to the first through third embodiments, the door lock switch 1₁ used for setting the ID registration mode is also used for determining the count value, but there is no particular need to use the same switch for these switches. Which switch is to be used for the determining of the three count values can be decided arbitrarily, and there is no difference distinguished according to which switch is operated. In this case, arranging such that the count value is determined by randomly selecting and operating the switches at the time of determining the three count values

Also, according to the first through third embodiments, the door lock switch 1₁ used for setting the ID registration mode is also used for determining the count value, but there is no particular need to use the same switch for these switches. Which switch is to be used for the determining of the three count values can be decided arbitrarily, and there is no difference distinguished according to which switch is operated. In this case, arranging such that the count value is determined by randomly selecting and operating the switches at the time of determining the three count values

does away
great can

On the other hand, as with the first through third embodiments, stipulating that only one switch is used can prevent an ID code being registered by unintentional operation of switches, and stipulating that particular switches be used for each of the three count determining operations allows ID code registration to be performed in an even more sure manner.

Further, an example has been described with regard to the first through third embodiments wherein the count of the counter 26 is stopped by operating a switch, and resetting the counter 26 each time determining of a count value is performed, but an arrangement may be made wherein the counter 26 is not reset but continues to count.

In this case, the cycle time for the count of the counter 2₆ can be set arbitrarily, but setting the cycle time at approximately 500 milliseconds allows early operations by the user to be dealt with sufficiently, and also allows ID code with excellent randomness to be registered.

The operating (lit) time and operating (lit) intervals shown in Figs. 3, 6, and 7, with regard to the first through third embodiments are nothing more than an example thereof, and the operating (lit) time and operating (lit) intervals

Next, Fig. 8 is an explanatory diagram illustrating an example of the operating procedures for writing the reference code to the reference code storing unit 10₁ of the receiver 20 using the portable transmitter 10 or portable transmitter 10'.

[illegible]

The user carries the portable transmitter 10, switches the ignition key 15 of the vehicle from the accessory (ACC) position to the on (ON) position, and supplies a key input pulse to the signal processing unit 12₁. Next, the user presses one of the switches of the operating switch unit 1 of the portable transmitter 10 within a time T1 from the key input pulse being supplied to the signal processing unit 12₁, and following the ID code "a" obtained by that operation being converted to a transmitting code, this is transmitted from the portable transmitter 10 as a transmitting signal. The receiver 20 receives this transmitting signal with the receiving unit 11 and supplies it to the signal processing

Next, within a time T3 from the stopping the supplying of the key input pulse in the first action cycle, the user operates the ignition key 15 and the switch of the portable transmitter 10 in the same manner as with the first action cycle, and the second action cycle is completed through the same action series as that of the first action cycle.

Next, the same operation is performed in the third action cycle and the fourth action cycle. In this case, in the fourth action cycle, the action form is the same as that of the first through third action cycles up to the extracting of the ID code "d" within the transmitting code with the signal processing unit 9₁ within the time T1 from the starting of supplying the key pulses, but the operating mode of the control unit 12 including the signal processing unit 12₁ is converted from the normal action mode to the reference code writing mode at the point that the time T4 has elapsed from stopping the supplying of the ID code "d",

~~d sub
rform~~

The operating procedures for writing the reference code are as follows.

Following the operating mode of the control unit 12 being converted to the reference code writing mode, the user operates the portable transmitter 10 for writing the reference code, transmits a transmitting code containing the ID code "e" as transmitting signals, and sends this to the receiver 20. At the point that the transmitting code is supplied to the signal processing unit 12₁ of the receiver 20 while the key input pulse is being supplied, the ID code "e" within the transmitting code is supplied to the reference code storing unit 13₁ as the reference code within the time T4 from the stopping of supplying the transmitting code, and the first reference code is written to the reference code storing unit 13₁. At this time, the fact that the writing of the reference code has been performed correctly is notified to the user by creating a door locked state or door unlocked state for a time T5.

Next, in the event that the user desires to write a reference (ID) code (second reference code) for another portable transmitter 10, the user operates this portable transmitter 10 in the same manner as the previous case, and writes the second reference code to the reference code

storing unit 13₁.

Subsequently, in the same way, in the event that there are other portable transmitters 10 to write reference code for, the user performs the same operating processes for writing reference code as above, which writes the reference codes to the reference code storing unit 13₁.

In this case, the control unit 12 automatically reverts from the reference code writing mode to the normal action mode following elapsing of a set time T6 from being set to the reference code writing mode.

In this case, suitable time ranges for the times T1, T2, T3, T4, T5, and T6 are shown in Fig. 8, but the times T1 through T6 are not necessarily restricted to the time ranges shown.

Incidentally, the above description is regarding a case wherein reference codes are written to the reference code storing unit 13₁ of the receiver 20 using portable transmitters 10, but reference codes can be written in the same manner using portable transmitters 10', as well.

Sub 222
Next, description will be made regarding the operation (normal operation) carried out between the portable transmitter 10 and the receiver 20 in the event that an ID code is registered in the ID code storing unit 4₁ of the portable transmitter 10 (or portable transmitter 10') and a reference code corresponding to the ID code is registered in

In the event that the user operates one of the operating switches on the operating switch unit 1, e.g., the door lock switch 1₁ for locking the doors of the vehicle, lock switch information indicating that the operation has been made from the lock switch 1₁ is output, and supplied to the function code converting unit 2₁. Upon receiving the lock switch information, the function code converting unit 2₁ converts the lock switch information into a corresponding function code and supplies this to the transmitting code forming unit 2₂. Once the function code is supplied, the transmitting code forming unit 2₂ adds to the function code ID code unique to the portable transmitter 10 read from the ID code storing unit 4₁, header code, end code, etc., thereby forming a transmitting code, and the formed transmitting code is supplied to the transmitting unit 3. The transmitting unit 3 forms transmitting signals of the supplied transmitting code being carried by wireless signals such as radio waves, and the transmitting signals are transmitted from the transmitting antenna 6.

On the other hand, once the receiver 20 receives the transmitting signals from the portable transmitter 10 with the receiving antenna 14, the transmitting signals are supplied to the receiving unit 11 as received signals, the receiving unit 11 restores the transmitting code within the

Also, in the event that other operating switches on the operating switch unit 1 are operated, e.g., the unlock switch 1₂ for unlocking the doors of the vehicle, function operations corresponding to the operating switch are carried out at the vehicle.

Incidentally, though the above description of the above embodiments has been made with reference to an example of a keyless entry device for the communication apparatus, the communication apparatus according to the present invention is by no means restricted to a keyless entry device; rather, the present invention can be applied to other apparatuses which have a portable transmitter and a receiver, and which

Thus, according to the first aspect of the present invention, ID code registration can be made from the portable transmitter by operation of the user, and in this case, the ID code to be registered is a random code due to the switch operation timing, so a portable transmitter wherein there is no compatibility between the portable transmitter of the user and the portable transmitters of others can be obtained.

Also, according to the second aspect of the present invention, the formed ID code sections are sequentially stored in a second storing unit formed of RAM, and at the point that all ID code sections are stored in the second storing unit, all ID code sections are joined and read out from the second storing unit, and transferred and registered as ID code to the first storing unit, so in the event that ID code registration has been aborted, all that is necessary is to erase the ID code sections stored in the RAM, so there is no effect on the first storing unit.

Also, according to the third aspect of the present invention, the formed ID code sections are sequentially stored in a second storing unit formed of RAM, and at the point that the last ID code section is formed, the ID code sections stored in the second storing unit are read out from the second storing unit and joined with the last ID code

Thus, the present invention is a communication apparatus that comprises a portable transmitter and a receiver. The portable transmitter includes at least one operating switch, a storing unit, a control unit, an ID registering mode setting mechanism and a transmitting unit. The storing unit contains an ID code that has ID code sections, each of which corresponds to an operation of the operating switch. The ID registering mode setting mechanism sets the control unit to an ID registration mode, and subsequently when the operating switch is operated the ID code sections are supplied to the storing unit to register as the ID code.

The portable transmitter may have an additional storage unit that stores either all of the ID code sections

In addition, the ID code sections may be sequentially supplied to the storing unit(s). The portable transmitter may also comprise a clock generating unit that generates clock signals and a counter that counts the clock signals and forms the ID code sections from the counter values. An LED or other mechanism may be used to notify the user of the storage state of the ID code sections.